

# VECTRONICS

## HPF-2 Deluxe High Pass Filter

Suppress television interference with Vectronics' new HPF-2 High Pass Filter for 75 Ohm TV system impedance.

- Use between cable and VCR or TV.
- Reduces signals received from transmitters operating below 30 MHz.
- Low loss in the TV passband 54 to 550 MHz.
- Unique shield blocking circuit configuration designed to prevent coax cable from acting like an HF antenna.

### SPECIFICATIONS

Passband:	54-550 MHz
Cutoff Frequency:	52 MHz
Attenuation:	-90dB at 10 MHz; -75dB at 20MHz; -60dB at 30 MHz
Impedance:	75 ohm unbalanced
Insertion Loss:	Less than 0.5dB @ 54-600 MHz
VSWR:	Less than 1.5: 1
Connectors:	CATV (Type F) 75ohm

### 75 OHM IMPEDENCE

